



COMMERCIAL

AE 1000 TELESCOPIC ANTENNA

FOR USE WITH TDR1000

SUPPLIED WITH

- > 1 x 6m telescopic antenna mast.
- > 1 x antenna support with ground stake & holding tube.
- > 1 x terminated antenna cable (N type connector) fixed to telescopic mast.
- > 1 x guy ring clip (no guy ropes supplied).
- > 1 x soft carry bag for collapsed antenna system.
- > 1 x whip antenna section (if ordered with product).
- > 1 x information leaflet.

If any items are missing or damaged, please contact your retailer or place of purchase.

PLEASE ENSURE THAT THE REPEATER IS SWITCHED OFF UNTIL ANTENNA IS CONNECTED

INSTALLATION

1. To erect the telescopic mast;
 - Remove antenna structure from the carry bag and identify whip antenna.
 - Unscrew top cap from the top end of the metal housing and attach whip antenna to the smallest telescopic section, place the metal cap into the bag.
 - Grasp the smallest section and extend to stop then twist and pull tightly.
 - Continue to extend, twist and pull tightly each section of the antenna till fully extended.If guy ropes are required, place the guy ring over the thin end of the antenna structure and slide to the larger sections till locked.

NOTE: Guy ropes/strings are not supplied however any small diameter nylon rope/string may be used if strong winds are expected. Normally the extended antenna will withstand wind velocities well in excess of 50 knots without the need for guying however prolonged use in very strong winds may eventually loosen the section grip. If strong winds are expected over long periods guying is recommended.

2. Slide the coaxial cable tail through the ground stake holding tube and place the extended structure into the holding tube ensuring that it fits comfortably into the two foam supports (one each end).
3. Attach the N type terminated cable to the repeater before operating the network.

DISMANTLE

1. Leave the extended antenna in the ground stake holding tube, turn off the repeater and disconnect the coaxial cable.
2. Twist and turn each section slowly collapsing the largest section to the smallest top section.
3. As each stage is collapsed, make sure that the antenna cable is retrieved from the base section to prevent the cable jamming within the telescopic tubes.
4. If used, remove the guy ring when that section is reached.
5. Remove the top whip section and place into the carry bag then replace the top cap on the top section of the metal housing.
6. Remove the coaxial cable through the ground stake holding tube.
7. Remove the ground stake and place over the collapsed antenna ensuring that the point faces the non-cable end.
8. Place the structure into the bag.
9. Lay the coaxial cable in loose lengths with each length being the same length as the carry bag.
10. Make sure all antenna parts are accounted for and returned to the carry bag.
11. Secure by zipping the bag.

STANDARD COMMUNICATIONS WARRANTY AGAINST DEFECTS

This warranty against defects is given by Standard Communications Pty Ltd ACN 000 346 814 (We, us, our or GME). Our contact details are set out in clause 2.7.

1. CONSUMER GUARANTEES

1.1 Our goods come with guarantees that cannot be excluded under the Australian Consumer Law. You are entitled to a replacement or refund for a major failure and for compensation for any other reasonably foreseeable loss or damage. You are also entitled to have the goods repaired or replaced if the goods fail to be of acceptable quality and the failure does not amount to a major failure.

1.2 To the extent we are able, we exclude all other conditions, warranties and obligations which would otherwise be implied.

2. WARRANTY AGAINST DEFECTS

2.1 This warranty is in addition to and does not limit, exclude or restrict your rights under the Competition and Consumer Act 2010 (Australia) or any other mandatory protection laws that may apply.

2.2 We warrant our goods to be free from defects in materials and workmanship for the warranty period (see warranty table) from the date of original sale (or another period we agree to in writing). Subject to our obligations under clause 1.2, we will at our option, either repair or replace goods which we are satisfied are defective. We warrant any replacement parts for the remainder of the period of warranty for the goods into which they are incorporated.

2.3 To the extent permitted by law, our sole liability for breach of a condition, warranty or other obligation implied by law is limited

(a) in the case of goods we supply, to any one of the following as we decide –

(i) the replacement of the goods or the supply of equivalent goods;

(ii) the repair of the goods;

(iii) the cost of repairing the goods or of acquiring equivalent goods;

(b) in the case of services we supply, to any one of the following as we decide –

(i) the supplying of the services again;

(ii) the cost of having the services supplied again.

2.4 For repairs outside the warranty period, we warrant our repairs to be free from defects in materials and workmanship for three months from the date of the original repair. We agree to re-repair or replace (at our option) any materials or workmanship which we are satisfied are defective.

2.5 We warrant that we will perform services with reasonable care and skill and agree to investigate any complaint regarding our services made in good faith. If we are satisfied that the complaint is justified, and as our sole liability to you under this warranty (to the extent permitted at law), we agree to supply those services again at no extra charge to you.

2.6 To make a warranty claim you must before the end of the applicable warranty period (see warranty table), at your own cost, return the goods you allege are defective, provide written details of the defect, and give us an original or copy of the sales invoice or some other evidence showing details of the transaction.

2.7 Send your claim to:

Standard Communications Pty Ltd.

PO Box 96 Winston Hills, NSW 2153, Australia.

Tel: (02) 8867 6000 Fax: (02) 8867 6199

Email: servadmin@gme.net.au

2.8 If we determine that your goods are defective, we will pay for the cost of returning the repaired or replaced goods to you, and reimburse you for your reasonable expenses of sending your warranty claim to us.

3. WHAT THIS WARRANTY DOES NOT COVER

3.1 This warranty will not apply in relation to:

(a) goods modified or altered in any way;

(b) defects and damage caused by use with non Standard Communications products;

(c) repairs performed other than by our authorised representative;

(d) defects or damage resulting from misuse, accident, impact or neglect;

(e) goods improperly installed or used in a manner contrary to the relevant instruction manual; or

(f) goods where the serial number has been removed or made illegal.

4. WARRANTY PERIOD

4.1 We provide the following warranty on GME and Kingray products. No repair or replacement during the warranty period will renew or extend the warranty period past the period from original date of purchase.

PRODUCT TYPE	WARRANTY PERIOD
Telemetry radio	2 years